

MTU Power Cable Installation

Refer to the MTU Installation Guide for detailed wiring instructions

1. Before checking the connections in the panel, be sure the power is off.
2. Make sure the black wire of MTU power cable is connected to a 15/20/30 Amp circuit breaker in the panel. After connecting, pull gently on wire to ensure it is tightly connected.
3. Make sure the white wire of MTU power cable is connected to the neutral bus in the panel. After connecting, pull gently on wire to ensure it is tightly connected.
4. Make sure the circuit breaker is turned ON.
5. If you have a voltmeter, confirm that the AC voltage from the black wire to the white wire is 110V to 125V.
6. Turn the power back on.